
SCALE 2:1



В


**DATE 13 MAY 2020** 


## NOTES

- DIMENSIONING AND TOLERANCING PER ASME
- DIMENSIDNING AND TOLERANCING PER ASME
  Y14.5M, 2009.
  CONTROLLING DIMENSION: MILLIMETERS
  DIMENSIONS D & E1 ARE DETERMINED AT DATUM
  H. DIMENSIONS DO NOT INCLUDE MOLD FLASH,
  PROTRUSIONS DR GATE BURRS. SHALL NOT
  EXCEED 0.23mm PER SIDE.
  LEAD DIMENSIONS & AND &1 DO NOT INCLUDE
  DAMBAR PROTRUSION. ALLOWABLE DAMBBAR
  PROTRUSION IS 0.08mm PER SIDE.
  DATUMS A AND B ARE DETERMINED AT DATUM H.
  A1 IS DEFINED AS THE VERTICAL DISTANCE
  FROM THE SEATING PLANE TO THE LOWEST
  POINT OF THE PACKAGE BODY.
  POSITIONAL TOLERANCE APPLIES TO DIMENSIONS
  & AND &1.

- b AND b1.


	MILLIMETERS			
DIM	MIN.	N□M.	MAX.	
Α			1.80	
A1	0.02	0.06	0.11	
b	0.60	0.74	0.88	
b1	2.90	3.00	3.10	
c	0.24		0.35	
D	6.30	6.50	6.70	
E	6.70	7.00	7.30	
E1	3.30	3.50	3.70	
е	2.30 BSC			
L	0.25			
į.	0°		10°	





= Assembly Location **GENERIC MARKING DIAGRAM\*** = Year = Work Week W XXXXX = Specific Device Code = Pb-Free Package AYW XXXXX=

(Note: Microdot may be in either location) \*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "•", may or may not be present. Some products may not follow the Generic Marking.



## RECOMMENDED MOUNTING FOOTPRINT

For additional information on our Pb-Free strategy and soldering details, please download the IN Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

DOCUMENT NUMBER:	98ASH70634A	Printed versions are uncontrolled except when accessed directly from the Document Repository.  Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.		
DESCRIPTION:	SOT-223		PAGE 1 OF 1	

ON Semiconductor and unare trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. ON Semiconductor does not convey any license under its patent rights nor the rights of others.